

CDS10-43-694/3800 10dB Directional Coupler

RFS CDS*-43 series Directional Coupler have been designed for a variety of wireless applications in the frequency band from 694 to 3800MHz. The unit couples off a defined fraction of a RF signal from 5 to 30 dB with minimal reflections or loss. The broad frequency range is ideally suited for multi-band distributed antenna systems or in combination with RADIAFLEX® radiating cables.



FEATURES / BENEFITS


- 4.3-10-female interfaces
- PIM optimized design (160dBc @2x43dBm)
- Low insertion loss
- High power handling
- Small size, Low weight

Technical features

STRUCTURE		
Product Type		Directional Coupler
Techn. Application		Indoor
Number of Input Ports		1
Number of Output Ports		2
ELECTRICAL SPECIFICATIONS		
Impedance	Ohm	50
Total Input Power	W	400
Frequency Range	MHz	694 - 3800
Connector Type		4.3-10 female
Max. VSWR / Return Loss	VSWR/dB	1.30/17.7 (1.3)
Insertion Loss max.	dB	0.7
Coupling Value	dB	10
Coupling Flatness max.	dB	±1.0
Intermodulation (IM3)		-160dBc (2x43dBm)
TEMPERATURE SPECIFICATIONS		
Temperature Range	°C (°F)	-25 to +65 (-13 to +149)
MECHANICAL SPECIFICATIONS		
Height	mm (in)	28.4 (1.12)
Width	mm (in)	69.2 (2.72)
Length	mm (in)	174.8 (6.88)
Weight	kg (lb)	0.45 (0.99)
TESTING AND ENVIRONMENTAL		
Environmental Class		IP65

REV DATE : 2020-04-08





External Document Links

Notes

Directivity: ≥ 20dB @ 694-2700MHz, ≥ 18dB @ 2700-3800MHz

REV DATE : 2020-04-08